



Festoon & Flood Lighting

• rules and procedures in force where people are at work may require the person responsible for this equipment to carry out a specific risk assessment.



Using the Lighting Equipment

Redistributed under licence from HAE by Hire Station Limited. Licence expires on 01/02/2021

- It is important to read all of this leaflet BEFORE using Festoon & Flood Lighting**

1. Plan each task and try to foresee any problems that may occur so they can be dealt with safely.

2. Electricity is dangerous and must always be used with great care.

3. Water and electricity make an extremely dangerous combination. Keep electrical equipment away from rain and water.

4. The following items of personal protective equipment are a minimum: rod if using a 230 volt (mains) supply.

5. Particular items of equipment or environments may require a higher level of personal protective equipment.

6. Lighting equipment must not be installed by minors, or by anyone under the influence of drugs or alcohol.

7. Lighting equipment is designed for installation by an able bodied adult. Anyone with either temporary or permanent disability must seek expert advice before using it.



If you have further questions or need more detailed information about HAE or our services, please contact us at the address below or by telephone.

HAE
The Crescent
Birmingham Business Park
Solihull B97 7YE

Tel: 0121 333 4109
Fax: 0121 333 4109
Email: mail@hae.org.uk
Website: www.hae.org.uk

1. Do not use electrical equipment where there is a danger of explosion. It may ignite fumes from petrol or gas cylinders.

2. Keep electrical equipment away from rain and water.

3. Ensure there are no combustible materials near floodlights. A floodlight can produce as much heat as a 1kw electric radiant heater and can cause paper and cloth to ignite. Check that no loose paper or rubbish can be blown into the area heated by the light.

4. For stand lights, choose an area where people are going to be safe from vehicles, people, water, rain, strong gusts of wind and other hazards which may damage them or knock them over. The ground should be firm and level.

5. For lights fixed to buildings or fixtures, make sure that their support is strong enough and secure. Take care to position lights up and away from where they may get struck by passing vehicles, people or materials being carried.

6. In all cases, plan cable runs to avoid damage to the cables, and so that the cables themselves do not form a tripping hazard in doorways or walkways.

7. In areas where members of the public are allowed, it may be necessary to put barriers around lighting stands to keep people away from the heat and to prevent them tampering with the light.

ELECTRICAL SAFETY - GENERAL

1. The equipment will only operate on one voltage; it will be 110v or 230v. 110v lighting will have a yellow industrial plug fitted. 230v lighting will have either a normal square pin plug fitted or a blue industrial plug. Read the instructions below for the equipment.

110 VOLT LIGHTING (YELLOW PLUG)

 - If using a portable transformer, plug the transformer directly into the 230 volt socket. Do not use any 230v extension cables.
 - Check the equipment cables, plugssockets and stands. If anything is damaged, do not use it – contact the hire company.
 - Check that the plugs on the cables match the supply. Do not try to force connections or improvise them.
 - Equipment with a cylindrical yellow industrial plug fitted is designed to run off a special 110v supply. The hire company will have provided a portable transformer if the equipment requires powering from a normal mains 230v supply. If a portable transformer has been supplied, take care not to injure yourself whether moving it about – it may be heavier than you think.
 - Equipment designed to run directly from 230v mains will have either a normal square pin plug fitted or a blue industrial plug.

WORK AREA

EQUIPMENT

- ## EQUIPMENT

Useful Reference Points • www.ltae.org.uk/businessguard

Before Starting Work...



CARTOON LIGHTS

HOTELING BULBS

- Do not connect more than four (4) festoon strings together unless the hire company has given specific instructions.

- When you have the correct replacement bulb ready, Check with your company if in any doubt.
 - Ensure no-one will put in any damage when switching off the lighting. The switch off and unplug the light.
 - High Power lights may need to cool before handling.
 - Open any covers taking care not to lose any fixing screws or clips.
 - Do not touch halogen bulbs with bare fingers – this will shorten the life of the bulb.
 - When the light bulb has been changed replace all covers and guards properly and secure any screws or clips.
 - Look away before plugging in a dazzling on as powerful lights can dazzle.

Any unauthorised reproduction – manually or electronically – is STRICTLY prohibited

©Copyright Hire Association Europe April 2011